





# PICK THE RIGHT CHARGER, AS EASY AS 1-2-3.

## STEP 1

Determine how many charging banks your trolling system requires. You need one charging bank for each battery (include your starting battery, if appropriate).



## STEP 2

Determine how fast of recovery/recharging time you require.

3 - 5 hours recovery time = 15 amps per bank

4 - 6 hours recovery time = 10 amps per bank

10 - 12 hours recovery time = 5 or 6 amps per bank

## STEP 3

Select the Minn Kota charger that best meets your needs from chart below.

## ON-BOARD CHARGER PRODUCT SPECIFICATIONS

ITEM #	DESCRIPTION	LENGTH	WIDTH	HEIGHT	WEIGHT (LBS)	# OF BANKS	OUTPUT PER BANK (AMPS)	TOTAL OUTPUT (AMPS)	RECOVERY TIME* (HOURS)
<b>1821060</b>	MK 106 On-Board Charger	8-3/4"	4-3/4"	3"	4.5	1	6	6	10-12
<b>1822100</b>	MK 210 On-Board Charger	11-1/2"	7-1/2"	4"	11	2	5	10	10-12
<b>1823150</b>	MK 315 On-Board Charger	12-1/2"	7-1/2"	4"	14	3	5	15	10-12
<b>1822200</b>	MK 220 On-Board Charger	13-1/2"	7-1/2"	4"	15	2	10	20	4-6
<b>1823300</b>	MK 330 On-Board Charger	16-1/4"	7-1/2"	4"	20	3	10	30	4-6
<b>1824400</b>	MK 440 On-Board Charger	21-1/2"	7-1/2"	4"	27	4	10	40	4-6
<b>1822300</b>	MK 230 On-Board Charger	11-3/4"	6-3/4"	7"	16.6	2	15	30	3-5
<b>1823450</b>	MK 345 On-Board Charger	11-3/4"	6-3/4"	8"	22	3	15	45	3-5
<b>1824600</b>	MK 460 On-Board Charger	14-1/2"	6-3/4"	8"	31	4	15	60	3-5

\*Approximate time to restore deep cycle batteries at 60% discharge.